ARK-JD3000

ARKEN GENERATOR



Life Goes On...

GENERATOR

Type - Phase	Open - Single
Voltage Regulate	AVR
Rated Frequency (Hz)	50
Rated AC Voltage (V)	230
Rated AC Output(kVA)	2,5kW
Peak AC Output(kVA)	2,8kW
Power Factor	COS¢=1

ENGINE

Model	C200
Туре	OHV Forced Air -Cooled 4 Strokes
Bore x Stroke (mm)	68x54
Dislancement (ml)	196
Max Output (Hp/rpm)	6.5 / 3600
Fuel	Unleaded Gasoline
Fuel Tank Capacity (I/gal)	15
Continuous Operanting Hours	11
Oil	SF or Higher Grade
İgnition System	T.C.I.
Starting System	Recoil Start
Operating System Level (7m)dB(A)	67

STANDARD FEATURES

Fuel Gauge	✓	-
Engine Switch	✓	
Voltmeter	✓	
AC Circuit Breaker	✓	
AC Socket	✓	
Pilot Lamb	✓	
Wheel Handle	2 x 6"	
Battery (for E-start)	-	
Hours Meter	+ 😕	
DC Output	✓	
DC Circuit Breaker	✓	

DIMENSIONS

Packing Dimensions (mm)	630x505x525	
Gross Weight (kg)	52	
Net Weight (kg)	50	