ARK-JD5000WH

ARCEN GENERATOR



Life Goes On...

GENERATOR

Type - Phase	Open - Single
Voltage Regulate	AVR
Rated Frequency (Hz)	50
Rated AC Voltage (V)	230
Rated AC Output(kVA)	4,0kW
Peak AC Output(kVA)	4,5kW
Power Factor	COS¢=1

ENGINE

Model	C390
Туре	OHV Forced Air -Cooled 4 Strokes
Bore x Stroke (mm)	88X64
Dislancement (ml)	389
Max Output (Hp/rpm)	13.0 / 3600
Fuel	Unleaded Gasoline
Fuel Tank Capacity (I/gal)	25
Continuous Operanting Hours	9
Oil	SF or Higher Grade
İgnition System	T.C.I.
Starting System	Recoil Start
Operating System Level (7m)dB(A)	72

STANDARD FEATURES

Fuel Gauge	✓
Engine Switch	✓
Voltmeter	1
AC Circuit Breaker	√
AC Socket	✓
Pilot Lamb	✓
Wheel Handle	2 x8 "
Battery (for E-start)	9Ah
Hours Meter	+ **
DC Output	√
DC Circuit Breaker	✓

DIMENSIONS

Packing Dimensions (mm)	735x575x635	
Gross Weight (kg)	86	
Net Weight (kg)	82	